Siemens OptiPoint - Display Telephones Quick Reference Guide Hi-Path 4000

GUIDANCE KEYS

(CONTROL THE "PROMPTS" IN THE DISPLAY)

Arrow keys are used to search for features:

- Press "►" to search for the next feature
- Press "◄" to search for the previous feature

Press "✓" to "Select" a feature

DIALING

- Lift the handset, press the "Speaker key" (or press the "Line"), to hear a dial tone.
- <u>Internal Call-</u> dial the "5" digit extension number.
- External Call- 9+1+(Area Code)+ 7 digit #

HOLD

To place a call on hold at your phone:

- Press the "**Hold**" key (line will flash)
- Hang up

To reconnect with the call:

• Press "Line key" next to flashing light

TRANSFER

To transfer a call to another extension:

 During a call, press "✓" at the "Start Transfer?" prompt.

(The caller will go on hold and you will hear a dial tone)

- 2. At the dial tone, dial the extension #
- 3. When answered, announce the caller then hang up (or simply "hang up")

To stop the transfer:

Press the "Connect" button

CONFERENCE (8 PARTY)

To set up a conference call:

1. While connected to a call, press "▶" until you see **"Start Conference?"** then press "✓"

(The caller will go on hold and you will hear a dial tone)

- 2. At the dial tone, dial the extension number or dial the outside number.

 (wait for an answer)
- Announce why you are calling, then press
 "✓" at the "Conference?" prompt

To add someone to a conference:

Press "✓" at the "Add to Conference?" prompt.

(The caller will go on hold and you will hear a dial tone)

- At the dial tone, dial the extension number or dial the outside number.
- Announce why you are calling then press
 "✓" at the "Conference?" prompt

If the party isn't going to join

Press "Connect" or press "▶" until you see
 "Release and return?" then press "√"

CALL FORWARD (LINE WILL FLICKER, WHEN ACTIVATED)

To forward your calls to another extension:

- 1. Get a dial tone, then dial "#-91" (Access Code)
- 2. Dial the extension to where you want your calls forwarded, press "✓" and hang up.
 - -To forward to voicemail dial **"816245"**To cancel forwarding calls:
- 1. Dial "#-#-91" (Access Code)

STATION PICKUP

To pick up another ringing extension, or to pick up a call placed on hold at another extension:

- 1. Lift the handset
- 2. Dial "***-3**" (Access Code)
- 3. Dial the extension #

GROUP PICKUP ("CONNECT" WILL FLASH)

To pick up a "ringing" call within your group (Pre-Programmed group of extensions):

- 1. Lift the handset
- 2. Press the "Connect" key

LAST NUMBER REDIAL

To redial the last call you made:

1. Get a dial tone. Screen will display "Last number redial?" Press "✓"

SAVED NUMBER REDIAL

To save a number for future redialing:

1. While on a call that <u>you made</u>, press "▶" until you see "**Save number?**" then press "✓"

To dial that number later:

Get a dial tone. Press "▶" until you see
 "Saved number redial" then press "√"

INTERCOM

To make an intercom call:

- 1. Press the "ICM" key
- 2. Dial the "2" digit intercom Extension you want to reach.

STATION SPEED DIAL (Personal List)

To store a speed dial:

- Press "▶" until you see
 "Program/Service?" then press "√".
- 2. You will then see **"Destinations?"**, then press "✓".
- 3. Press "▶" until you see "**Speed Dial Features?"** then press "✓".
- 4. At "**Enter index**", dial index code (00-19)
- 5. At "**Enter Destination**", dial "9-1-(area code)" plus the number that you wish to store, then press "✓".

To dial your number:

- 1. Press the "Sta-Spd" key
- 2. At "**Enter index**" prompt dial index code (00-29)

To Program R-Key (Repdial)

To program a "1" number "Speed Dial"

- At an idle phone, press "▶" until you see "Program/ Service?", then press "√"
- 2. Press an available "**R-Key**" (labeled "R-")
- 3. Dial the number that you wish to store
- 4. At "**Save?**" press "✓"

Preview (caller I.D. for 2nd call)

If another line on your phone starts to ring (while you are on a call)

1. Press the "**Preview**" button (will blink red) then press the button next to the line that is ringing. (The telephone number will show in the display)

To Answer the new call

• Hang up or put 1st call on "Hold". Then make sure that the "**Preview**" button is not "blinking" (if it is, press it again!) Then answer the new call.

AUDIO SETTINGS

No dial tone needed!

To adjust ring volume:

- Press "+" key. Display will show "Ringer Volume?" Press "✓"
- 2. Press "+" or (-) key to adjust ring volume. Press "✓" to store.

To adjust ring tone:

- Press (+) key, press "▶" until you see "Ringer Pitch?" Press "√"
- 2. Press (+) or (-) key to adjust ring tone. Press "✓" to store.

SPEAKER PHONE & MUTE

For a hands-free conversation:

• Press "Speaker" and hang up

To mute the microphone (Handset or Speakerphone):

• Press "Mute" (Press again to "un-mute")